

наті 🛄 🔝 🖏 😭

msi

msi

C847MS-E83





# MAINBOARD

# C847MS-E33

- Onboard Intel<sup>®</sup> Celeron<sup>®</sup> Processor 847
- Support DDR3-1333MHz Memory
- Support USB 2.0 & SATA 6Gb/s

#### **Key Features**

**F84** 

### All Solid CAPs

Longer lifespan than electrolytic

capacitors

• Endurable to operate under higher

frequency & temperature





## SATA 6Gb/s

• SATA 6Gb/s has a 2x higher

transmission speed than SATA 3Gb/s

Best performance with new HDDs and SSDs





#### **M-Flash**

- It allows all the BIOS information to backup and update on a USB drive
- Rebuild all the BIOS information the

original state for convenient, safe repairs



	M-Flash
== BIOS Update or Load BIOS From USB drive ==	
M-Flash function as	[USB Drive ]
Load BIOS source file form [US	B:Ut161 USB2Flas
======================================	
Save File to Selected Device [US	3B:Ut161 USB2Flas]
Save File Name as	[A75201MS]
Save Extend File name as	[10]]
Start to save file	[Press Enter]

## Specifications





Processor	Onboard Intel® Celeron® Processor 847
Memory	2 DIMMs support for DDR3-1066/1333MHz up to 16GB max
Video	<ul> <li>1 x PCI-Express 2.0 x16 slot</li> <li>Support Intel® HD Graphics with integrated HDMI/D-Sub video ports</li> </ul>
Audio	8-channel (7.1) HD Audio subsystem
LAN	10/100/1000 Mb/s LAN subsystem
Peripheral interfaces	<ul> <li>1 x SATA 6Gb/s port from NM70.</li> <li>3 x SATA 3Gb/s ports from NM70</li> <li>8 x USB 2.0 ports (4 Rear / 4 Front)</li> </ul>
Expansion capabilities	<ul> <li>1 x PCI-Express x1 slot</li> <li>2 x PCI slots</li> </ul>
Form Factor	Micro-ATX

## шшш. msi. com